

TECHNICAL DATA

# Fluke 9062 Motor and Phase Rotation Indicator



## Key features

- 3 phase indication
- Indication of phase rotation
- Indication of motor rotation direction
- Contact free determination of the rotation direction of running motors

## Product overview: Fluke 9062 Motor and Phase Rotation Indicator

### Unique phase rotation indicator with motor rotation ability

The unique Fluke 9062 provides rotary field and motor rotation indication with the benefits of contact-less detection. Purpose made for commercial and industrial environments, the Fluke 9062 provides rapid indication of 3 phase rotation using test leads supplied or can be used to determine motor rotation on synchronous and asynchronous 3 phase motors. The contact-less detection is ideal for use on motors where the shaft is not visible. The included test probes have a variable clamping range for safe contact, also in industrial sockets.

## Specifications: Fluke 9062 Motor and Phase Rotation Indicator

Technical specifications	
Voltage range	Up to 400 V
Phase display	120-400 V AC

Frequency range	2-400 Hz
Operating timer	Continuous
<b>Environmental specifications</b>	
Operating temperature	0 °C to 40 °C
Operating altitude	Up to 2000m
Humidity (without condensation)	15% to 80%
Dust/water resistance	IP 40
<b>Safety specifications</b>	
Electrical safety	EN 61010,
	EN 61557-7
Overvoltage category	CAT III, 300 V
<b>Mechanical and general specifications</b>	
Size	124 x 61 x 27 mm
Weight	1 x 9 V
Batteries	1 x 9 V
Warranty	2 years

## Ordering information



### **Fluke 9062 Motor and Phase Rotation Indicator**

Fluke 9062 Motor and Phase Rotation Indicator

- Test leads (3)
- Test probes (3)
- Alligator clips (3)
- Battery, 9 V
- User manual

**Fluke.** *Keeping your world up and running.®*

**Fluke Corporation**  
PO Box 9090, Everett, WA 98206 U.S.A.

**For more information call:**  
In the U.S.A. (800) 443-5853  
In Canada (800) 36-FLUKE  
From other countries +1 (425) 446-5500  
[www.fluke.com](http://www.fluke.com)

©2023 Fluke Corporation.  
Specifications subject to change without notice.  
05/2023

**Modification of this document is not permitted  
without written permission from Fluke Corporation.**