

SOCKET TESTER
SE-09



FEATURES :

- ✓ LCD DISPLAY
- ✓ DATA HOLD
- ✓ THREE HOLE SOCKET LINE SEQUENCE DETECTION
- ✓ PHASE VOLTAGE (L_N) MEASUREMENT
- ✓ LEAKAGE VOLTAGE (N_E) MEASUREMENT
- ✓ RCD (OF GFCI) TEST
- ✓ SOCKET SEQUENCE TEST
- ✓ AUTOMATIC SHUTDOWN FUNCTION
- ✓ TO DETECT WIRING ERROR
- ✓ TRIP TIME TEST



AC Voltage



Back light



Detect wiring Error



Three hole socket line sequence detection



Leakage Trip Detection



Two colour backlight



300V

SPECIFICATION	RANGE
VOLTAGE RANGE	AC 30~260V / 45~65Hz ±(3.0%+2)
LEAKAGE VOLTAGE RANGE	0~99V/45~65Hz, ±(2.0%+2)
TRIP TIME TEST	20~1000mS ±(1.0%+4)
RCD TEST	>30mA
VOLTAGE MEASUREMENT	48V~250V/45~65Hz
SOCKET CONNECTION DETECTION	Correct Connection
	Open Ground
	Open Neutral
	Open Live
	Live Wire and Ground Wire Reverse
	Live Wire and Neutral Wire Reverse
SIZE	H67 x W65 x D61 mm
	POWER
DC1.5V x 2AAA	