

SOCKET TESTER SE-09

HTC
HAZARI TECH CONNECT



FEATURES :

- ☒ LCD DISPLAY
- ☒ DATA HOLD
- ☒ THREE HOLE SOCKET LINE SEQUENCE DETECTION
- ☒ PHASE VOLTAGE (L_N) MEASUREMENT
- ☒ LEAKAGE VOLTAGE (N_E) MEASUREMENT
- ☒ RCD (OF GFCI) TEST
- ☒ SOCKET SEQUENCE TEST
- ☒ AUTOMATIC SHUTDOWN FUNCTION
- ☒ TO DETECT WIRING ERROR
- ☒ TRIP TIME TEST



SPECIFICATION	RANGE
VOLTAGE RANGE	AC 30-260V / 45-65Hz $\pm(3.0\%+2)$
LEAKAGE VOLTAGE RANGE	0-99V/45-65Hz, $\pm(2.0\%+2)$
TRIP TIME TEST	20-1000mS $\pm(1.0\%+4)$
RCD TEST	>30mA
VOLTAGE MEASUREMENT	48V-250V/45-65Hz
SOCKET CONNECTION DETECTION	Correct Connection
	Open Ground
	Open Neutral
	Open Live
	Live Wire and Ground Wire Reverse
	Live Wire and Neutral Wire Reverse
	Live Wire and Ground Wire Reverse Missing ground wire
SIZE	H67 x W65 x D61 mm
POWER	DC1.5V x 2AAA